

The New Era for Printing

P2509 Series

## Simply Smart.

Print high quality documents on-the-go with the compact printer that is easy to use and easy to carry. Enjoy connectivity, space saving and budget friendly features from the mini printer that SMB, home users and office professionals rely on.



**BUSINESS READY ECONOMICAL PRINTER SERIES** 

•1600 pages starter cartridge •Silvery-grey sleek exterior



One-Step Driver Installation and Direct Printing



Compact Size and Sleek Design



Office Document Direct Print from Mobile Devices



Fast Print Speed

WiFi and print from mobile device available for P2509W



## **KEY SPECIFICATIONS**



## P2509 Series

Available in ■Grey

Technology	Electrophotographic monochrome laser
Print speed	22 ppm (A4) / 23 ppm (Letter)
First print out time	Less than 7.8s
Maximum Monthly Duty Cycle	8,000 pages
Recommended monthly volume	2,000 pages
Resolution(dpi)	Max. 1,200×1,200
Printer language	GDI
Duplex Mode	Manual
PER HANDLING	
Paper input	150 pages
Paper output	100 pages
Paper output	Plain, Thick, Transparency, Cardstock, Label, Envelope, Thin
Mediasize	A4, A5, A6, JIS B5, ISO B5, B6, Letter, Legal, Executive, Statement, Monarch envelope, DL envelope, C5 envelope, C6 envelope, NO.10 envelope, Japanese postcard, Folio, Oficio, Big 16k, 32k, 16k, Big 32k, ZL, Yougata4, Postcard, Younaga3, Nagagata3, Yougata2
Media weight	60~163g/m²
NERAL	
Dimensions (WxDxH)	337 x 220 x 178 mm (13.27" x 8.66" x 7.01")
Weight (with cartridge)	4.75kg (10.47lbs)
Recommended environment	Temperature range: 10-32°C (50°F-90°F) Humidity range: 20% - 80%
Power	110V Model: AC100~127V (±10%); 50Hz/60Hz; 6A 220V Model: AC220~240V (-15%,+10%), 50Hz/60Hz; 3A
Power	
	220V Model: AC220~240V (-15%,+10%), 50Hz/60Hz; 3A  Printing: 52 dB
Noise	220V Model: AC220~240V (-15%,+10%), 50Hz/60Hz; 3A  Printing: 52 dB Standby: 30 dB  Printing: Average 370W Ready: 38W
Power consumption  Operating system compatibility  Mobile Operating system	220V Model: AC220~240V (-15%,+10%), 50Hz/60Hz; 3A  Printing: 52 dB Standby: 30 dB  Printing: Average 370W Ready: 38W Sleep Mode: Less than 2W  Microsoft Windows Server2003/Server2008/Server2012/XP Vista/Win7/Win8/Win8.1/Win10 (32/64 Bit) Mac OS 10.7-10.15
Power consumption  Operating system compatibility  Mobile Operating system compatibility	220V Model: AC220~240V (-15%,+10%), 50Hz/60Hz; 3A  Printing: 52 dB Standby: 30 dB  Printing: Average 370W Ready: 38W Sleep Mode: Less than 2W  Microsoft Windows Server2003/Server2008/Server2012/XP Vista/Win7/Win8/Win8.1/Win10 (32/64 Bit) Mac OS 10.7-10.15 Linux (Ubuntu 12.04&14.04&16.04&18.04) (32/64 Bit)    iOS 7.0 and above;
Power consumption  Operating system compatibility  Mobile Operating system compatibility  Connectivity	220V Model: AC220~240V (-15%,+10%), 50Hz/60Hz; 3A  Printing: 52 dB Standby: 30 dB  Printing: Average 370W Ready: 38W Sleep Mode: Less than 2W  Microsoft Windows Server2003/Server2008/Server2012/XP Vista/Win7/Win8/Win8.1/Win10 (32/64 Bit) Mac OS 10.7-10.15 Linux (Ubuntu 12.04&14.04&16.04&18.04) (32/64 Bit)  iOS 7.0 and above; Android 4.4 and above
Noise Power consumption	220V Model: AC220~240V (-15%,+10%), 50Hz/60Hz; 3A  Printing: 52 dB Standby: 30 dB  Printing: Average 370W Ready: 38W Sleep Mode: Less than 2W  Microsoft Windows Server2003/Server2008/Server2012/XP Vista/Win7/Win8/Win8.1/Win10 (32/64 Bit) Mac OS 10.7-10.15 Linux (Ubuntu 12.04&14.04&16.04&18.04) (32/64 Bit)  iOS 7.0 and above; Android 4.4 and above  Hi-Speed USB 2.0

Toner cartridge(1)

PD-219 (Standard capacity toner: 1,600 pages)

## WHAT'S IN THE BOX

Printer x 1/ 1600 pages starter cartridge x 1 / USB interface cable x 1 / Power cord x 1 / CD-ROM x 1 / Quick setup guide x 1

(1) As per ISO/IEC 19752 specification (Individual users will experience different results based on their environment and page coverage)

Copyright © 2019 Pantum International Limited. The information contained herein is subject to change without notice. Pantum shall not be liable for technical or editorial errors or omissions contained herein.
\*Printer data based on Pantum internal testing.